



POWER BRIGHT
YOUR LEADER IN POWER SOLUTIONS

MODEL
ERP3500-12

SPECIFICATION SHEET

3500 Watt 220V/50Hz 12 Volt DC Power Inverter



This heavy duty 220V / 50Hz inverter plugs directly to a 12 Volt DC battery to power EUROPEAN 20V/50Hz microwaves, power tools and electronics in your vehicle!

This unit has the following features:

- 3500 watts continuous power
- 7000 watts peak power
- Provides 15.9 Amps
- Anodized aluminum case provides durability
- LED Display- Input Voltage/Output Wattage
- Built-in Cooling Fan
- Internal, Replaceable 30 Amp spade-type Fuses
- Double Universal 220 volt AC outlet (EUROPEAN OUTLET)
- Overload Indicator
- Power ON/OFF Switch

Optimum efficiency	up to 90%
No-load draw	< 1.2 amp
Output Wave Form	Modified Sinewave
Input voltage range	10-15 VDC
Over voltage shutdown	over 15 VDC
Under voltage shutdown	under 10 VDC
Low voltage alarm	Audible
Overload shutdown	Yes
Thermal shutdown	Yes
Short circuit shutdown	Yes
AC receptacle	2 - Universal receptacles
Warranty	1 year
Inverter weight	28.00 lbs
Dimensions (W x H x D)	9 x 6.25 x 19.25 in.

CE RoHS
COMPLIANT

MODEL
ERP3500-12
SPECIFICATION SHEET

www.PowerBright.com
© 2010 PowerBright . All rights reserved