



**POWERBRIGHT**  
YOUR LEADER IN POWER SOLUTIONS

MODEL  
PW1100-12

SPECIFICATION SHEET

## 12V DC to AC 1100 Watt Power Inverter



This inverter plugs directly to a 12 Volt DC battery to power laptops, televisions, gaming consoles and other electronics and small appliances in your vehicle

**This unit has the following features:**

- 1100 watts continuous power
- 2200 watts peak power
- Provides 9.2 Amps
- Anodized aluminum case provides durability
- Built-in Cooling Fan
- External, Replaceable 30 Amp spade-type Fuses
- Dual 3 Prong 120 volt AC outlet
- Overload Indicator
- Power ON/OFF Switch
- LED Display- Input Voltage/Output Wattage



Optimum efficiency	up to 90%
No-load draw	< 0.18 amp (12V)
Output Wave Form	Modified Sinewave
Input voltage range	10-15 VDC
Over voltage shutdown	over 15 VDC
Under voltage shutdown	under 10 VDC
Low voltage alarm	Audible
Overload shutdown	Yes
Thermal shutdown	Yes
Short circuit shutdown	Yes
AC receptacle	2 - three-prong receptacle
Warranty	1 year
Inverter weight	4.00 lbs
Dimensions (W x H x D)	5.8 x 2.8 x 11.25 in.
Weight	6 lbs.

MODEL  
PW1100-12  
SPECIFICATION SHEET

www.PowerBright.com  
© 2010 PowerBright . All rights reserved